



Myers MSS-AK-PIR1 is a wireless PIR motion sensor operating on 433 MHz and 315 MHz radio frequencies. The device provides detection coverage up to 8 meters with a 110-degree detection angle when wall-mounted. It features flash alarm notification and transmits signals up to 80 meters. Powered by a single 9V 6F22 battery with 250 mAh capacity, the sensor draws 40 µA idle current and 15 mA peak current. The plastic housing measures 110 × 53 × 37.3 mm and weighs 80 grams. Operating temperature ranges from -20°C to 40°C with humidity tolerance of 20-95% RH non-condensing.

Podrobnosti o produktu	
Model	MSS-AK-PIR1
SKU	7951
Specifikace	
Rádiová frekvence	433 MHz, 315 MHz
Přenosová vzdálenost	80 m
Elektrické specifikace	
Klidový proud	≤ 40 µA
Špičkový proud	≤ 15 mA
Specifikace alarmů	
Režim alarmu	Blikající alarm
Mechanické specifikace	
Detekční vzdálenost	8 m
Způsob instalace	Zed'
Detekční úhel (stěna)	110°
Materiál krytu	Plastik
Rozměry	110 x 53 x 37.3 mm
Hmotnost	80 g
Síla	

Typ baterie	9V (6F22) × 1
Kapacita baterie	250 mAh
Provozní podmínky	
Rozsah vlhkosti	20-95% RH (neeskondenzující)
Prevádzková teplota	-20 - 40 °C
Teplota skladování	-30 - 50 °C
Běžný	
Záruka	3 roky