



Myers MSS-AK-PIR1 is a wireless PIR motion sensor operating on 433 MHz and 315 MHz radio frequencies. The device provides detection coverage up to 8 meters with a 110-degree detection angle when wall-mounted. It features flash alarm notification and transmits signals up to 80 meters. Powered by a single 9V 6F22 battery with 250 mAh capacity, the sensor draws 40 µA idle current and 15 mA peak current. The plastic housing measures 110 × 53 × 37.3 mm and weighs 80 grams. Operating temperature ranges from -20°C to 40°C with humidity tolerance of 20-95% RH non-condensing.

Dettagli del prodotto	
Modello	MSS-AK-PIR1
SKU	7951
Specifiche	
Radiofrequenza	433 MHz, 315 MHz
Distanza di trasmissione	80 m
Specifiche elettriche	
Corrente a riposo	≤ 40 µA
Corrente di picco	≤ 15 mA
Specifiche allarme	
Modalità allarme	Allarme flash
Specifiche meccaniche	
Distanza di rilevamento	8 m
Metodo di installazione	Parete
Angolo di rilevamento (parete)	110°
Materiale di alloggiamento	Plastica
Dimensioni	110 x 53 x 37.3 mm
Peso	80 g
Potenza	

Tipo di batteria	9V (6F22) × 1
Capacità della batteria	250 mAh
Condizioni operative	
Fascia di umidità	20-95% RH (non condensante)
Temperatura di esercizio	-20 - 40 °C
Temperatura di stoccaggio	-30 - 50 °C
Comune	
Garanzia	3 anni